2017年 NOLTAソサイエティ大会 IEICE, NOLTA 愛知, 2017年6月10日

# N

# Synchronization Phenomena of Coupled Two Rings of Chaotic Circuits

Katsuki Nakashima

Kazuki Ueta

Yoko Uwate

Yoshifumi Nishio

Tokushima University

## 1 Introduction

Nonlinear phenomena of coupled chaotic circuits are drawing attention from many researchers. In this study, we investigate synchronization phenomena of coupled two rings of chaotic circuits. In addition, we observe the synchronization phenomena by changing the coupling strength.

### 2 System Model

The chaotic circuit is shown in Fig. 1 and the system model is shown in Fig. 2. In this study, we couple three chaotic circuits on the ring structure and we propose a system model that the two rings are coupled via a resistor. One ring chaotic circuit generates chaotic attractors and the other ring generates three-periodic attractors. Then, we focus on synchronization phenomena of the chaotic circuits.



The normalized circuit equations of the system are given as follows:

$$\begin{cases} \frac{dx_i}{d\tau} = \alpha x_i + z_i, \\ \frac{dy_i}{d\tau} = z_i - \frac{1}{2} \left( \left| y_i + \frac{1}{\delta} \right| - \left| y_i - \frac{1}{\delta} \right| \right), \\ \frac{dz_i}{d\tau} = -x_i - \beta y_i - \sum_{\substack{i,j=1\\i,j=1\\(i,j=1,2,\cdots,6)}}^{6} \gamma_{ij}(z_i - z_j) \\ (i,j=1,2,\cdots,6), \end{cases}$$
(1)

where  $\gamma$  is the coupling strength. We define  $\alpha_c$  to generate the chaotic attractor, and  $\alpha_p$  is defined to generate the three-periodic attractors.

#### **3** Simulation Results

We set the parameters of the system as  $\alpha_c = 0.460$ ,  $\alpha_p = 0.412$ ,  $\beta = 3.0$  and  $\delta = 470.0$ . Figure 3 shows attractor of each chaotic circuit and Fig. 4 shows the difference of voltage waveform when we set the coupling strength as  $\gamma = 0.001$ . CC5 and CC6 are synchronized. Figure 5 shows attractor of each chaotic circuit and Fig. 6 shows the difference of voltage waveform when we set the coupling strength as  $\gamma = 0.23$ . Synchronous and asynchronous states change with the simulation time. Here, we make a comparison the circuits between CC1 - CC2 and CC5 - CC6. We can say that the circuits of CC1 and CC2 are more synchronized than the circuits of CC5 and CC6.



#### 4 Conclusions

In this study, we have proposed a system model that the two rings of chaotic circuits are coupled via a resistor. We have investigated synchronization phenomena by increasing the coupling strength. As a result, we confirmed that synchronous and asynchronous states of chaotic solutions changed with the simulation time when the coupling strength  $\gamma$  is set to 0.23.